



Description

The i³™ sounder and relay smoke detectors apply the guiding principles of installation ease, intelligence, and instant inspection in a series of specialty conventional devices.

Installation ease.

Throughout the i³ series, installation is simple with its installer-friendly base and plug-in design. The base accommodates a broad range of back box and direct mounting options, and provides ample space for pre-wiring the installation. To complete the installation, the i³ detector plugs into its base with a simple Stop Drop 'N Lock action.

Intelligence

To reduce the likelihood of nuisance alarms, all i³ detectors are equipped with both drift compensation and smoothing algorithms. These capabilities minimize both short- and long-term causes of nuisance alarms such as RF interference and dust accumulation. When connected to the C2W-MOD2A loop test /maintenance module or an i³ Ready™ panel, 2-wire i³ detectors can generate a remote maintenance signal when they are in a maintenance or freeze trouble condition. To measure the sensitivity of any i³ detector, the CSENS-RDRA displays the reading, in terms of percent per foot obscuration, within seconds.

Instant inspection

The i³ line's red and green LEDs simplify local status indication during power-up, standby, alarm, maintenance and freeze trouble conditions. When in alarm, i³ sounder models generate an 85dB temporal tone. If connected to the CRRS-MODA reversing relay/synchronization module, all i³ sounders on the loop will activate when one detector is in alarm. Additionally, the CRRS-MODA synchronizes the output of all i³ sounders, to ensure a clear audible signal. Should the application call for differentiating between a local and a general alarm, the i³ line offers an isolated thermal model, which initiates a local alarm when smoke is detected, and a general alarm when the thermal sensor is activated.

Features

- Full line of options including:
 - 85 dB sounder
 - Form C relay
 - Isolated thermal sensor
- Maintains the i³ feature set including:
 - Plug-in design
 - Mounting base included
 - In-line terminals
 - Mounts to octagonal, single gang and 4-square back boxes, or direct to the ceiling
 - Stop-Drop 'N Lock™ attachment to the base
 - Removable cover and chamber
 - Remote maintenance signaling
 - Drift compensation and smoothing algorithms
 - Simplified sensitivity measurement
 - Dual color LEDs
 - EZ Walk loop testing

Engineering Specifications

Smoke detector shall be an i³ Series model listed to Underwriters Laboratories UL 268 for Fire Protection Signaling Systems. The detector shall be a combination photoelectric/thermal equipped with a sounder (model C2WTA-BA, C4WTA-BA), a Form C relay (model C2WTR-BA), a combination sounder/relay (model C4WTAR-BA) or an isolated thermal/sounder/relay (model C4WITAR-BA). The detector shall include a mounting base for mounting to 3½-inch and 4-inch octagonal, single gang, and 4-inch square back boxes with a plaster ring, or direct mount to the ceiling using drywall anchors.

Wiring connections shall be made by means of SEMS screws. The detector shall allow prewiring of the base and the head shall be a plug-in type. The detector shall have a nominal sensitivity of 2.5% per foot nominal as measured in the UL smoke box. The detector shall be capable of automatically adjusting its sensitivity by means of drift compensation and smoothing algorithms. The detector shall provide dual color LED indication which blinks to indicate power up, normal standby, out of sensitivity, alarm, and freeze trouble conditions. When used in conjunction with the A2W-MOD2A module, 2-wire models shall include a maintenance signal to indicate the need for maintenance at the alarm control panel, and shall provide a loop testing capability to verify the circuit without testing each detector individually. When used in conjunction with the CRRS-MODA module, all i³ sounder models on a loop shall sound when one alarms, all shall be synchronized, and all sounders may be silenced from the panel.



Electrical Specifications

Operating Voltage

Nominal: 12/24 V non-polarized
2-wire: 8.5 V - 35 V
4-wire: 10 V - 35 V

Peak Standby Current

2-wire: 100 μ A
4-wire: n/a

Maximum Alarm Current

2-wire: 130 mA limited by control panel
4-wire: C4WTA-BA, C4WTR-BA: 35 mA
C4WTAR-BA, C4WITAR-BA: 50 mA

Maximum Ripple Voltage

30% of applied (peak to peak)

Alarm Contact Ratings

2-wire: n/a
4-wire: 0.5 A @ 30V AC/DC

Standby Current

2-wire: 50 μ A maximum average
4-wire: 50 μ A maximum average

Form C Contact Ratings

2A @ 30V AC/DC

LED Modes

LED Mode	Green LED	Red LED
Power up	Blink every 10 secs	Blink every 10 secs
Normal (standby)	Blink every 5 secs	off
Out of sensitivity	off	Blink every 5 secs
Freeze trouble	off	Blink every 10 secs
Alarm	off	Solid

Power Up Sequence for LED Indication

Condition	Duration
Initial LED status indication	80 seconds

Physical Specifications

Operating Temperature Range

32°F–100°F (0°C–37.8°C)

Sensitivity

2.5%/ft. nominal

Weight

7.1 oz. (200 grams)

Operating Humidity Range

0 to 95% RH non-condensing

Input Terminals

14–22 AWG

Mounting

- 3½-inch octagonal back box
- 4-inch octagonal back box
- Single gang back box
- 4-inch square back box with a plaster ring
- Direct mount to ceiling

Thermal Sensor

135°F (57.2°C) fixed

Dimensions (including base)

5.3 inches (134 mm) diameter
2.0 inches (51 mm) height

Freeze Trouble

41°F (5°C)

Ordering Information

Model Number

C2WTA-BA
C2WTR-BA
C4WTA-BA
C4WTR-BA
C4WTAR-BA
C4WITAR-BA

Thermal

Yes
Yes
Yes
Yes
Yes
Yes

Wiring

2-wire
2-wire
4-wire
4-wire
4-wire
4-wire

Alarm Current

130 mA max. limited by control panel
130 mA max. limited by control panel
35 mA
35 mA
50 mA
50 mA

Accessories

CRRS-MODA
C2W-MOD2A
CSENS-RDRA
A77-AB2
RT

i3 Series Reversing relay/synchronization module
i3 Series 2-wire loop test/maintenance module
i3 Series Sensitivity Reader
i3 Series Retrofit Adapter Bracket
i3 Series Removal/Replacement Tool

NOT TO BE USED FOR INSTALLATION PURPOSES.



Canada

25 Interchange Way
Vaughan, Ontario L4K 5W3
Telephone: (905) 660-4655
Fax: (905) 660-4113

U.S.A.

4575 Witmer Industrial Estates
Niagara Falls, NY 14305
Toll Free: (888) 660-4655
Fax Toll Free: (888) 660-4113

Distributed by:

