



## Description

The RAM-3500-LCD Remote Annunciator is used as a component of an FX-3500 and FX-401 Fire Alarm System. It provides an exact mimic of the FX-3500 and FX-401 displays at a remote location.

The display is 4 lines by 20 characters back-lit alphanumeric LCD. It displays information regarding the panel, its circuits, and devices. An on-screen cursor is controlled by the cursor buttons for menu selection and control.

## Features

- Durable membrane tactile switches
- 4 line, 20 character back-lit alphanumeric LCD display.
- Common feature LEDs and push buttons.
- Alphanumeric keypad for the LCD.
- Each RAM-3500-LCD has its own address. Addresses available are 1 to 7 inclusive.
- Control switches provided for System Reset, Signal Silence, Fire Drill and Acknowledge, four Status Queues with selector switches and LEDs for Alarm, Supervisory, Trouble and Monitor, along with a numeric keypad to access the menu functions..
- Mounted occupying one display position of the BB-1000 series enclosures.

## Electrical Ratings

<b>Power Limited Nominal Voltage:</b> 24 VDC	
<b>Current Consumption:</b>	
Standby:	70 mA
Alarm:	100 mA

## Ordering Information

Model	Description
RAM-3500-LCD	Remote LCD Annunciaor

