

LT-9280 Set-up Notes For TX3-TOUCH Series Telephone Entry Panels

Caution: To ensure a proper installation extreme care must be taken during the initial set-up.

For all touch screens

- Be careful not to reposition the microphone and ensure the top of the microphone is level with the surface of the chassis preventing it from touching any metal surfaces.
- Do not change the speaker and microphone settings in the **Calls** tab of the **Panel Configuration** window of the TX3 Configuration and Monitoring Utility. The **Speaker** is set at 5, and the **Mic** is set at 11.
- Use a “line interactive” UPS supply, if possible, to protect against transients, spikes, and power loss (for example, Order Minuteman ETR500).
- Follow the proper shutdown procedure and **NEVER** remove power to reset the system.

Proper Shut Down Procedure

To shut down the TX3 unit from the touch screen software, perform the following steps.



Note: Never disconnect the power or turn off the power when the system is running.

1. At the Touch Screen terminal, enter 9999.
2. Enter your administrator password, and then press **OK**.
3. Select **File > Shut Down > Shut Down**.
4. Do not disconnect the power until the full shut down process has been completed.