



Features

Input Power on AC	3-4W
Output Power on Battery	1W
Lamp Type	LED strip
Input Voltage	120-347 VAC
Frequency	50/60 Hz
Battery Type	NI-Cd
Working Time	180 Minutes
Charging Time	24 Hours

Description

- Durable 20 gauge steel housing
- 2-sided sign
- Wall, side and ceiling mountable
- Input Voltage: 120 - 347VAC 50/60Hz
- LED technology
- 3.6V 1000mAh Nickel Cadmium battery
- Test switch and charge indicator light
- Overcharge & Over-discharge protection
- Backup time: 180 minutes
- Suitable for damp locations
- Operating Temperature: 5 °C ~ 30 °C / 41 °F ~ 86 °F

Technical Drawing



Included Pictograms



With Arrow 2 pcs



Without Arrow 1 pc

Ordering Information

Model	Description
ELRM-100S	Steel LED Running Man Sign with Battery Backup



Canada
 25 Interchange Way Vaughan, ON L4K 5W3
 Telephone: (905) 660-4655 | Fax: (905) 660-4113

U.S.A.
 4575 Witmer Industrial Estates Niagara Falls, NY 14305
 Toll Free: (888) 660-4655 | Fax Toll Free: (888) 660-4113



THIS INFORMATION IS FOR MARKETING PURPOSES ONLY AND NOT INTENDED TO DESCRIBE THE PRODUCTS TECHNICALLY.

For complete and accurate technical information relating to performance, installation, testing and certification, refer to technical literature. This document contains intellectual property of Mircom. The information is subject to change by Mircom without notice. Mircom does not represent or warrant correctness or completeness. All rights reserved. All other trademarks and registered trademarks are properties of their respective owners.