



BB-5008



BB-5014

Features

- Backbox made from 16 gauge cold rolled steel
- Door is made from 14 gauge steel
- All cabinet doors come with fire retardant lexan window
- Includes the universal CAT-30 lock and 2 keys
- All cabinet doors come hinged to the left side of the backbox and can easily be moved to the right side if necessary. This allows doors to be opened and the operator can reach all displays in multiple enclosure installations.
- UL 864, 9th addition listed & ULC

Description

Mircom's BB-5008 and BB-5014 Lobby Control Enclosures support the FX-2000, and Flex-Net series. The door and chassis hardware are ordered separately for quick & easy installation. Enclosures provide spacing for internal lobby control modules and are available with either white or red doors for aesthetically pleasing and complementary design options.

The BB-5008 and BB-5014 are compatible with:

- FX-2009-12DS (FX-2000)
- FX-2009S-12DS (FX-2000 large build)
- FX-2009-12NDS (Flex-Net)

The BB-5008 is a lobby control centre enclosure capable of handling one FX-2009-12DS Large Main Control Unit which supports 2 internal annunciator modules such as the IPS-2424DS, FDX-008W/KI, RAX-1048TZDS, etc. (See installation manual). In addition, the BB-5008 allows for 4 footprints for mounting Audio Lobby Control modules, Fire Fighter's Lobby Control modules and FX-2000 Internal Annunciator modules. The cabinet hold up to 24 AH batteries

The BB-5014 is a lobby control centre enclosure capable of handling one FX-2009-12DS Large Main Control Unit which supports 2 internal annunciator modules such as the IPS-2424DS, FDX-008W/KI, RAX-1048TZDS, etc. In addition, the BB-5014 allows for 10 footprints for mounting Audio Lobby Control modules, Fire Fighter's Lobby Control modules and FX-2000 Internal Annunciator modules. The BB-5014 can also support a graphic annunciator in place of these modules. The cabinet holds up to 24 AH batteries.



Ordering Information

Model	Description
Enclosures	
BB-5008	Lobby Control Center Enclosure (36" H x 30" W x 7" D). Supports 8 Module Footprints.
BB-5014	Lobby Control Center Enclosure (60" H x 30" W x 7" D). Supports 14 Module Footprints.
Doors	
DOX-5008M	White Metal Door for BB-5008-White
DOX-5008MR	Red Metal Door for BB-5008-Red
DOX-5014M	White Metal Door for BB-5014-White
DOX-5014MR	Red Metal Door for BB-5014-Red
Mounting Kit	
CCH-5008-ANNUNKIT	Mounting kit for BB-5008 Annunciator configurations. One per BB-5008 enclosure.
CCH-5008-PANELKIT	Mounting kit for BB-5008 Panel configurations. One per BB-5008 enclosure
CCH-5014-ANNUNKIT	Mounting kit for BB-5014 Annunciator configurations. One per BB-5014 enclosure
CCH-5014-PANELKIT	Mounting kit for BB-5014 Panel configurations. One per BB-5014 enclosure.



Canada
 25 Interchange Way
 Vaughan, Ontario L4K 5W3
 Telephone: (905) 660-4655
 Fax: (905) 660-4113

U.S.A.
 4575 Witmer Industrial Estates
 Niagara Falls, NY 14305
 Toll Free: (888) 660-4655
 Fax Toll Free: (888) 660-4113



THIS INFORMATION IS FOR MARKETING PURPOSES ONLY AND NOT INTENDED TO DESCRIBE THE PRODUCTS TECHNICALLY.

For complete and accurate technical information relating to performance, installation, testing and certification, refer to technical literature. This document contains intellectual property of Mircom. The information is subject to change by Mircom without notice. Mircom does not represent or warrant correctness or completeness.