



BB-5008



BB-5014

Description

Mircom's BB-5008 and BB-5014 Lobby Control Enclosures support the Flex-Net series. The door and backbox parts are ordered separately. Enclosures provide spacing for internal lobby control modules and are available in either red or black doors.

The BB-5008 and BB-5014 are compatible with:

- FX-4009-12N and FX-2009-12NDS (Flex-Net)

The BB-5008 is a lobby control centre enclosure capable of handling one FX-4009-12N and FX-2009-12NDS Large Main Control Unit which supports 2 internal annunciator modules such as the IPS-2424DS, FDX-008W/KI, RAX-1048TZDS, etc. (See installation manual). In addition, the BB-5008 allows for 4 footprints for mounting Audio Lobby

Features

- Backbox made from 16 gauge cold rolled steel
- Door is made from 14 gauge steel
- All cabinet doors come with fire retardant Lexan® window
- Includes the universal CAT-30 lock and 2 keys
- All cabinet doors come hinged to the left side of the backbox and can easily be moved to the right side if necessary. This allows doors to be opened and the operator can reach all displays in multiple enclosure installations.

Control modules, Fire Fighter's Lobby Control modules and Internal Annunciator modules. The cabinet holds up to 42 AH batteries.

The BB-5014 is a lobby control centre enclosure capable of handling one FX-4009-12N and FX-2009-12NDS Large Main Control Unit which supports 2 internal annunciator modules such as the IPS-2424DS, FDX-008W/KI, RAX-1048TZDS, etc. In addition, the BB-5014 allows for 10 footprints for mounting Audio Lobby Control modules, Fire Fighter's Lobby Control modules and Internal Annunciator modules. The BB-5014 can also support a graphic annunciator in place of these modules. The cabinet holds up to 24 AH batteries.



Ordering Information

Model	Description
Enclosures	
BB-5008	Lobby Control Center Enclosure (36" H x 30" W x 7" D). Supports 8 Module Footprints.
BB-5014	Lobby Control Center Enclosure (60" H x 30" W x 7" D). Supports 14 Module Footprints.
Doors (Optional)	
DOX-5008MB	Black Metal Door for BB-5008-Black
DOX-5008MR	Red Metal Door for BB-5008-Red
DOX-5014MB	Black Metal Door for BB-5014-Black
DOX-5014MR	Red Metal Door for BB-5014-Red
Mounting Kit	
CCH-5008-ANNUNKIT	Mounting kit for BB-5008 Annunciator configurations. One per BB-5008 enclosure.
CCH-5008-PANELKIT	Mounting kit for BB-5008 Panel configurations. One per BB-5008 enclosure.
CCH-5014-ANNUNKIT	Mounting kit for BB-5014 Annunciator configurations. One per BB-5014 enclosure.
CCH-5014-PANELKIT	Mounting kit for BB-5014 Panel configurations. One per BB-5014 enclosure.



Canada

25 Interchange Way Vaughan, ON L4K 5W3
Telephone: (905) 660-4655 | Fax: (905) 660-4113

U.S.A.

4575 Witmer Industrial Estates Niagara Falls, NY 14305
Toll Free: (888) 660-4655 | Fax Toll Free: (888) 660-4113

This document is provided by Mircom Technologies Ltd., MGC Systems Corp., or their affiliates, subsidiaries and brands, for convenience or marketing only and does not describe products or services technically. For technical information refer to technical manuals. We do not make representations or warranties regarding this information, including as to completeness or accuracy. We may change these contents at any time and reserve all rights in the contents, including copyrights, trademarks and other intellectual property. All other trademarks and registered trademarks are properties of their respective owners.