



MIX-4020 / MIX-4020-ISO

Description

The MIX-4020/MIX-4020-ISO multi-sensor detector is a hardwired sensor with an integral microprocessor that continuously monitors the environment to provide early warning of a fire condition and communicates with the panel using a fully digital protocol.

The MIX-4020/MIX-4020-ISO provides a higher level of nuisance alarm rejection as compared with single-criteria sensors leveraging both smoke and heat sensing elements.

The MIX-4020/MIX-4020-ISO works with an MGC compatible control panel supporting high rates of information exchange with reliable and secure bi-directional communication.

The detector is addressed and programmed using the MIX-4090 hand-held device. Addresses can be selected from a range of 1 -240.

This detector ships with a dust cover to protect the device during installation and prior to commissioning.

Two tri-color LEDs on the device provide 360 degrees of status visibility.

A remote LED indicator can be wired directly to the sensor.

The Multi-Sensor Detector transmits an analog representation of smoke density and temperature over a communication line to the compatibly listed Fire Alarm Control Panel. The FACP is able to illuminate LED display points based on the values received from the sensor. The LED indications can be displayed for three (3) temperature ranges, below 90°F or 100°F, between 90°F or 100°F and 135°F, and above 135°F. This can be used for Fire Service Access Elevator (FSAE) display (Temperature sensing per NFPA 72 2019 21.5).

Features

- Any combination of MIX-4000 series devices up to 240 can be connected on a single SLC.
- Different LED colors for Alarms and Troubles.
- Detection of smoke using advanced software algorithms using complementary thermal sensor.
- Advanced protection against nuisance alarms caused by dust, insects or other debris
- Multiple sensitivity settings.
- Compatible with the full series of MIX-4000 input and control modules.
- The device can be secured by a unique Anti-Tamper feature.
- The address is set with the hand-held device programmer (MIX-4090)
- MODEL OPTION - Built-in short-circuit isolator (MIX-4020-ISO)

Benefits

- Open style mounting bases offer easy wiring and low pressure locking.
- 4" or 6" base options available.
- Remote output can be controlled by the panel.
- MIX-4020-ISO is equipped with a bi-directional short-circuit isolator to protect against wiring faults and loop failure.
- Low standby current.
- Base has detachable tab for labeling device address.
- Leverages interrupts to quickly report alarm conditions to fire alarm control panels.
- Magnet test option helps with commissioning and maintenance.



Technical Specifications

Normal Operating Voltage	15 to 30VDC
Maximum Alarm Current	3.2mA (LED on)
Standby Current	160µA
UL/ULC Listed Temperature Range	32°F to 100°F (0°C to 37.8°C)
Operating Temperature	15°F to 120°F (-9°C to 49°C)
Humidity	10% to 93% Non-condensing
Wiring range on terminals	22 to 12 AWG
Diameter	4.25"
Height	1.75"

Detector LED colors		Description
RED (Steady on)		ALARM condition
GREEN (Flash)		NORMAL condition
AMBER (Steady on)		FAULT condition
Heat Detection Settings		
135°F (57°C)		
135°F with rate of rise as per UL268		
Sensitivity Level	Typical	Note
LEVEL 1	2.0%/FEET	Most Sensitive level
LEVEL 2	2.5%/FEET	Sensitivity level
LEVEL 3	3.0%/FEET	Sensitivity level
LEVEL 4	3.5%/FEET	Least Sensitive Level

Ordering Information

Model	Description
MIX-4020	Multi-Criteria/Multi-Sensor (Non-Isolated)
MIX-4020-ISO	Multi-Criteria/Multi-Sensor (with built-in short circuit isolator)
MIX-4001	6" Detector Base
MIX-4002	4" Detector Base
MIX-4003-S	Sounder Base
MIX-4003-R	Relay Base
MIX-4003-LF	Low Frequency Sounder Base
MIX-4090	MIX-4000 Series Addressable Device Programmer



Canada

25 Interchange Way Vaughan, ON L4K 5W3
Telephone: (905) 660-4655 | Fax: (905) 660-4113

U.S.A.

4575 Witmer Industrial Estates Niagara Falls, NY 14305
Toll Free: (888) 660-4655 | Fax Toll Free: (888) 660-4113

www.mircom.com

This document is provided by Mircom Technologies Ltd., MGC Systems Corp., or their affiliates, subsidiaries and brands, for convenience or marketing only and does not describe products or services technically. For technical information refer to technical manuals. We do not make representations or warranties regarding this information, including as to completeness or accuracy. We may change these contents at any time and reserve all rights in the contents, including copyrights, trademarks and other intellectual property. All other trademarks and registered trademarks are properties of their respective owners.

CAT. 9502

Rev. 9