

# LT-6077 Replacing the MD-1105 Power Supply and Audio Mixer Board

1. At the Touch Screen terminal, enter 9999.
2. Enter your administrator password, and then press **OK**.
3. Select **File > Shut down > Shut down**.
4. Disconnect the power from the Touch Screen.
5. Turn off the current power supply and audio mixer board with the switch on the board.
6. Disconnect the power cable from TS11 on the current board.
7. Disconnect the ribbon cable from P5 on the current board.
8. Disconnect all input, output, and networking harnesses from the current board.
9. Unscrew the four #8-32 screws that hold the current board in place.
10. Remove the current board and replace it with the new MD-1105 main controller board.
11. Secure the new board with the four screws you removed in step 9.
12. If there are any daughter boards attached to the old board, remove them, and then install them on the new board.
13. Connect all the input, output, and networking harnesses that you removed in step 8 to the new board.
14. Connect the ribbon cable to P5 on the new board.
15. Connect the power harness to TS11 on the new board.
16. Turn on the new board.
17. Reconnect power to the Touch Screen and turn it on.

