



Description

Mircom's PTR-2000-1 Remote Line Printer is designed to work with a compatible Intelligent Fire Alarm Control Unit. The printer is able to produce a printed record of all events occurring in the system. Small and compact, the PTR-2000-1 Remote Line Printer is the ideal supplement to the system.

The PTR-2000-1 is simple to install. The unit must be plugged into a local 120 VAC isolated power source. It connects to the main panel or a Remote Shared Display via an RS-232C interface connection.

Mircom provides an interface connection kit that contains the following items:

- 1 - 10ft. standard RS-232 cable
- 1 - 6ft. 9-pin to 25-pin AT serial cable
- 1 - 9-pin to 9-pin gender changer
- 1 - AC Cheater Plug 120V

The interface connection kit is required to connect the PTR-2000-1 to a compatible main panel or the Remote Shared Display. The PTR-2000-1 must be located within 50 feet of either the main panel or Remote Shared Display.

Features

- Connects to a compatible main panel or a Remote Shared Display via an RS-232C interface connection
- Compact Design
- Simple Installation
- Requires 120 VAC power source
- Tractor Feed
- Dot Matrix
- Serial Input

Specifications

Power:	120 VAC, 60 Hz
Interface:	RS-232C
Baud Rate:	9600 bits/second
Operating Temp:	5°C to 35°C (41°F to 95°F)
Relative Humidity:	10 to 80%
Dimensions:	5.8"H x 14.4"W x 10.8"D (147mm H x 366mm W x 275mm D)
Weight:	9.8 lbs (4.4 kg)

Paper Type

Cut Sheets:

Width: 3.9" - 10.1" (100mm - 257mm)

Length: 3.9" - 14.3" (100mm - 364mm)

Continuous Paper:

Width: 4" - 10" (101.6mm - 254mm)

Length: 4" - 22" (101.6mm - 558.8mm)

Roll Paper:

Width: 8.5" (216mm)

Wiring Diagrams

PTR-2000-1 connected to a compatible Main Control Unit



RS-232C
Interface
Connection
using the
supplied Interface
Connection Kit



PTR-2000-1

120 VAC

Note: *PTR-2000-1 must be located within 50 feet of the main unit.*

PTR-2000-1 connected to a Remote Shared Display



RS-232C
Interface
Connection
using the
supplied Interface
Connection Kit



PTR-2000-1

120 VAC

Note: *PTR-2000-1 must be located within 50 feet of the Remote Shared Display*

Ordering Information

Model

PTR-2000-1

Description

Remote Line Printer with Interface Connection Kit

NOT TO BE USED FOR INSTALLTION PURPOSES.



MircomTM

Canada

25 Interchange Way
Vaughan, Ontario L4K 5W3
Telephone: (905) 660-4655
Fax: (905) 660-4113

U.S.A.

4575 Witmer Industrial Estates
Niagara Falls, NY 14305
Toll Free: (888) 660-4655
Fax Toll Free: (888) 660-4113

Web page: <http://www.mircom.com>

Email: mail@mircom.com

Distributed by:

ISO 9001:2008
REGISTERED



CAT. 5922
Rev.5